

#### FICHE PRODUIT - SHOKV1

# Manual call point green 1 contact English language



# Détails techniques

Input voltage	-
Contact	NO+NC
Buzzer	No
Cover	Yes
Indicator light	No
Reset	Front/On the bottom



Pour visualiser la fiche produit sur notre site internet, cliquez-ici

#### SHOKV1 manual call point 1 contact

The SHOK® manual call point range developed and assembled inFrance by SEWOSY, was especially intended to suit the needs of installers. Whatever the situation, you can be sure to meet perfectly your needs.

Multiple benefits make this product unique on the market:

- an exclusive design thanks to the « Diamond » texture of its front face, giving an original and elegant aspect,
- double reset possibility on front or below. The front option is more ergonomic; indeed, several devices can be installed successively, one above the other, without disturbing their reset,
- a key holder located on the rear, on both sides of the surface mounting box, in order to stock the 2 keys included in the packaging and minimize the risk of loss,
- cable entry on the top, with pre-drilling for cable duct,
- improved LED lighting.

#### Technical specifications:

1 C/NO/NC contact with high switching rate, enhancing its resistance (the switch can better withstand high

intensities provided by other devices: locks, electromagnetic locks...)

Operating voltage: 12/24V DC (+10%)

Consumption: 12V DC max. 45 mA / 24V DC max. 62 mA

Switching rate: 250V AC - 5 A / 30V DC - 4 A

Protection rating: IP40 (indoor use) Operating temperature: 0 to +50°C

Locking by central screw

Surface or flush mounting on 60 mm mounting box

Protection Cover included

Available languages: French, English, Spanish, Portuguese, Italian and Dutch

The product range includes the versions **1 contact SHOKV1** or 2 contacts, as well as two models with buzzer/LED. One of them is equipped with a new fonctionality: the cover opening detection, associated to a specific white LED.

# Articles complémentaires



# SHOK C

Protection cover for manual call point SHOKV1 - SHOKV2 - SHOKV3 series



# SHOK K

Reset key for manual call point SHOK series



### SHOK P

Plastic seal green for SHOK series